

Conformity to CE and UL

Compliance to EC and EMC Directives

EC Directives

The EC Directives apply to all such electronic products as those having specific functions and have been exported to EU and directly sold to general consumers. Those products are required to conform to the EU unified standards and to furnish the CE marking on the products.

MINAS AC Servos conforms to the EC Directives for Low Voltage Equipment so that the machine incorporating our servos has an easy access to the conformity to relevant EC Directives for the machine.

EMC Directives

MINAS Servo System conform to relevant standard under EMC Directives setting up certain model (condition) with certain locating distance and wiring of the servo motor and the driver. And actual working condition often differs from this model condition especially in wiring and grounding. Therefore, in order for the machine to conform to the EMC Directives, especially for noise emission and noise terminal voltage, it is necessary to examine the machine incorporating our servos.

Conformed Standards

Subject	Conformed Standard			
Motor	IEC60034-1	IEC60034-5	UL1004 CSA22.2 No.100	Conforms to Low-Voltage Directives
	EN50178	UL508C	CSA22.2 No.14	
Motor and driver	EN55011	Radio Disturbance Characteristics of Industrial, Scientific and Medical (ISM) Radio-Frequency Equipment		Conforms to references by EMC Directives
	EN61000-6-2	Immunity for Industrial Environments		
	IEC61000-4-2	Electrostatic Discharge Immunity Test		
	IEC61000-4-3	Radio Frequency Electromagnetic Field Immunity Test		
	IEC61000-4-4	Electric High-Speed Transition Phenomenon/Burst Immunity Test		
	IEC61000-4-5	Lightening Surge Immunity Test		
	IEC61000-4-6	High Frequency Conduction Immunity Test		
	IEC61000-4-11	Instantaneous Outage Immunity Test		

IEC : International Electrotechnical Commission
 EN : Europaischen Normen
 EMC : Electromagnetic Compatibility
 UL : Underwriters Laboratories
 CSA : Canadian Standards Association

Composition of peripheral components


<Precautions in using options>

Use options correctly after reading operation manuals of the options to better understand the precautions.

Take care not to apply excessive stress to each optional part.

Installation environment

Use Minas driver in environment of Pollution Degree 1 or 2 prescribed in IEC-60664-1(e.g. Install the driver in control panel with IP54 protection structure.)




Power supply

100V system : Single phase 100V	+10%	-15%	-115V	+10%	-15%	50/60Hz
200V system : Single phase 200V	+10%	-15%	-240V	+10%	-15%	50/60Hz
200V system : 3- phase 200V	+10%	-15%	-240V	+10%	-15%	50/60Hz

- (1) Use the power supply under an environment of Overvoltage Category III specified in IEC60664-1.
- (2) For a interface power supply, use the insulated one with 12 to 24 VDC which conforms to CE Marking or EN Standards (EN60950).


Circuit breaker

Connect a circuit breaker which conforms to IEC standards and is UL recognized (UL Listed,  marked), between the power supply and the noise filter.

Noise filter

When you install one noise filter in the power supply for multi axis application, consult with the manufacture of the filter.

Option part No.	Part No.	Manufacturer
DV0P4160	3SUP-HU10-ER-6	Okaya Electric Industries Co.





Surge absorber

Install a surge absorber at primary side of the noise filter.

Option part No.	Driver voltage spec	Part No.	Manufacturer
DV0P1450	3-phase, 200V	R · A · V-781BXZ-4	Okaya Electric

Option part No.	Driver voltage spec	Part No.	Manufacturer
DV0P4190	Single phase, 100V, 200V	R · A · V-781BWZ-4	Okaya Electric




<Remarks>

Remove this surge absorber when you perform dielectric test on the machine, or surge absorber might be damaged.

Noise filter for signal lines

Install noise filters for signal lines to all cables (Power line, motor cable, encoder cable, interface cable)

Option part No.	Part No.	Qty.	Manufacturer
DV0P1460	ZCAT3035-1330	4	TDK Corp.



<Caution>

Fix the signal line noise filter in place to eliminate excessive stress to the cables. (Refer to page E-9 [Composition of peripheral equipment])

Grounding

- Connect the protective earth terminal of the driver (⊕) and protective earth terminal of the control panel (PE) without fail to prevent electrical shocks.
- Do not co-clamp to the ground terminals (⊕). Two ground terminals are provided.

Ground-fault breaker

Install a B-type ground-fault breaker (RCD) at primary side of the power supply of the driver.

Conformity to UL Standards

Observe the following conditions ((1) and (2)) to make the system to conform to UL508C (File No. E164620).

- Use Minas driver in environment of Pollution Degree 1 or 2 prescribed in IEC-60664-1. (e.g. Install in the control panel with IP54 protective structure)
- Connect the UL recognized (UL Listed, marked) circuit breaker or UL recognized (UL Listed, marked) fuse between the power supply and noise filter.